

EUROLITE FD-8 DMX dimmer panel

DMX lighting controller 8 channels

Art.n.: 70063806

GTIN: 4026397298956



L'articolo non è più disponibile.

Features :

- 8 channel faders with LED
- Fade time fader with LED for adjusting the step time
- Master fader with LED for adjusting the total output level
- Speed fader for adjusting the program-speed
- Flash button per channel and master-flash
- LED display of all modes
- 4 freely programmable programs with up to 84 steps each
- Controller comes with 4 pre-programmed chasers
- The programs and chasers can be called up individually or combined (CH1-2-3-4-PR-1-2-3-4)
- Dimmer: manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout function
- Program speed adjustable via speed fader or tap sync button
- Sound-control via external signal or integrated microphone
- Sound to light via 6.3 mm jack
- Power supply via included power unit
- Only for professional use

Logistica

EAN / GTIN: 4026397298956

Peso : 1,94 kg

Lunghezza : 0.46 m

Larghezza : 0.23 m

Altezza : 0.15 m

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 1,00 W

Pila: 1 x 9.0 V E block (non in dotazione)

Misure:	Larghezza: 33 cm Profondità: 13,5 cm Altezza: 7 cm
	via 9-15 V DC, 300 mA power unit included in the delivery
	or 1 standard 9 V battery
Battery life:	approx. 3 hours
Number of control channels:	8
Integrated chasers:	4
Free programs:	4 x 84 scenes
Sound-control:	via built-in microphone or via audio-input
Audio-input:	Jack
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector
Dimensions (L x W x H):	330 x 135 x 70 mm
Weight:	1.75 kg