

FUTURELIGHT WDS-G4 TX Wireless-DMX-Transceiver

Wireless DMX system 2.4 GHz - compact transceiver with W-DMX unit by Wireless Solution

Art.n.: 51834022

GTIN: 4026397588958

L'articolo non è più disponibile.

Features :

- Wireless transmission of DMX data
- Switching between transmitter and receiver
- Compatible with Wireless Solution W-DMX systems
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- AFHSS technology ensures interference-free operation also alongside other DMX transmitters and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Simultaneous operation of up to 6 transmitters, thus control of 6 DMX universes (3072 DMX channels) possible
- 1 to 512 receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button
- LED indication for operation and functions
- DMX input and output, 3-pin XLR
- Truss attachment option
- 2.4 GHz - license-free worldwide
- Può ricevere ed elaborare fino a 512 canali DMX
- Può inviare fino a 512 canali DMX
- Controllabile via DMX; W-DMX by wireless solution
- Portata fino a 500m a vista
- 2.4 GHz registrazione gratuita e gratuita in tutto il mondo
- Fino a 6 trasmettitori possono funzionare in parallelo senza interferenze
- Latenza estremamente bassa

Dotazione della fornitura

- 1 x Dispositivo, 1 x Cavo di rete/Cavo di alimentazione, 1 x Clip di fissaggio, 1 x Manuale d'uso, 1 x dichiarazione di conformità, 1 x Antenna

Logistica

EAN / GTIN: 4026397588958

Peso : 1,10 kg

Lunghezza : 0.21 m

Larghezza : 0.17 m

Altezza : 0.10 m

Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz
Potenza totale installata:	3 W
Grado di protezione:	IP20
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite P-Con (blu), versione da incasso cavo di alimentazione con spina di protezione (in dotazione)
Canali DMX:	Ingresso 512 Uscita 512
Ingresso DMX:	1 x XLR (M) a 3 poli versione da incasso
Uscita DMX:	1 x XLR (F) a 3 poli versione da incasso
Attivazione:	DMX; W-DMX by wireless solution
Massima:	Fino a 500m a vista
Banda di frequenza:	2.4 GHz
Deviazione della portante:	2,4 GHz
Sistema parallelo:	Massima 6 Trasmettitore
Latenza:	< 5 ms
Modulazione:	AFHSS
Colore:	Nero
Misure:	Larghezza: 14,5 cm Profondità: 10 cm Altezza: 5,8 cm
Peso:	0,93 kg