

EUROLITE FD-512 DMX Dimmer Panel

Handy DMX controller for 512 channels

Art.n.: 70063815

GTIN: 4026397512229



L'articolo non è più disponibile.

Features :

- Compact DMX controller for convenient operation of light effect units with DMX512 interface (e.g. spotlights and dimmers)
- Simply connect and operate, requires no extensive programming
- 512 control channels
- 8 channel faders for adjusting the DMX values in 64 groups
- Internal memory for 1 scene
- Flash push-button with LED
- Flash time adjustable (0.1s-10min)
- Blackout push-button with LED
- 2 x 16-digit LCD screen
- 3-pin and 5-pin XLR connectors
- Mounting frame for rack installation available as accessory
- Power supply via included power unit
- Può inviare fino a 512 canali DMX
- Controllabile via DMX
- Custodia per mixer

Logistica

EAN / GTIN: 4026397512229

Peso : 1,50 kg

Lunghezza : 0.40 m

Larghezza : 0.23 m

Altezza : 0.12 m

Dati tecnici :

Alimentazione elettrica:	100-240 V AC, 50/60 Hz
--------------------------	------------------------

Potenza totale installata:	1,00 W
----------------------------	--------

Grado di protezione:	IP20
----------------------	------

Canali DMX:	Uscita 512
-------------	------------

Attivazione:	DMX
Colore della custodia:	Nero
Colore:	Nero
Struttura della custodia:	Custodia per mixer
Misure:	Larghezza: 17,8 cm Profondità: 29,2 cm Altezza: 5,9 cm
Peso:	1,25 kg
	via included power unit
Number of control channels:	512
DMX512 output:	3-pin and 5-pin XLR connector
Dimensions (L x W x H):	292 x 178 x 59 mm